

PX319

PX319-HV

Driver LED C.C. 1 x 2A

Driver LED C.C. 1 x 1,5A/hv

User manual



# Table of Contents

|  |    |
|--|----|
| 1 Description.....                     | 3  |
| 2 Safety conditions.....               | 3  |
| 3 Connectors and control elements..... | 5  |
| 4 DMX indicator light meanings.....    | 5  |
| 5 DMX address setting.....             | 6  |
| 5.1 Smooth function settings.....      | 7  |
| 5.2 No Signal function settings.....   | 7  |
| 5.3 PWM frequency settings.....        | 8  |
| 6 Driver output current setting.....   | 8  |
| 6.1 Temperature control.....           | 10 |
| 7 DMX signal connecting.....           | 11 |
| 8 Connection scheme.....               | 12 |
| 9 Dimensions.....                      | 13 |
| 10 Technical data.....                 | 14 |

*Manufacturer reserves the right to make modifications in order to improve device operation.*

PXM Marek Żupnik sp.k.  
Podłęże 654  
32-003 Podłęże  
BDO register number 000005972

tel. +48 12 385 83 06  
mail: [info@pxm.pl](mailto:info@pxm.pl)  
[www.pxm.pl](http://www.pxm.pl)

Rev.1-4  
22.09.2021

# 1 Description

---

The PX319 driver is designed to control LEDs. Can be powered with voltage 12 – 48V DC (version PX319) or 12 – 60V DC (version PX319-HV) and a maximum current-carrying of 2A (PX319) or 1,5A (PX319-HV). It is possible to set the driver output current according to the parameters of receivers LED.

PX319 can be controlled by the DMX signal (the device has a built-in DMX-512 receiver) or it can work independently. DMX address is set manually via a DIP switch on the housing. The user also has the ability to set one of the eight levels of brightness with which the LEDs will be triggered in the absence of a DMX signal.

## 2 Safety conditions


---

PX319 is a device powered with safe voltage of 12 – 48V DC (version PX319-HV 12 – 60V DC); however, during its installation and use the following rules must be strictly observed:

1. The device may only be connected to 12 – 48V DC (version PX319-HV 12 – 60V DC) with current-carrying capacity compatible with technical data.
2. All the conductors should be protected against mechanical and thermal damage.
3. In the event of damaging any conductor, it should be replaced with a conductor of the same technical data.
4. Connection of DMX signal can only be made with shielded conductor.

5. All repairs and connections of outputs or DMX signal can only be made with cut off power supply.
6. The PX319 should be strictly protected against contact with water and other liquids.
7. All sudden shocks, particularly dropping, should be avoided.
8. The device cannot be turned on in places with humidity exceeding 90%.
9. The device cannot be used in places with temperature lower than +2°C or higher than +40°C.
10. Clean with damp duster only.

### 3 Connectors and control elements





### 4 DMX indicator light meanings

The driver is equipped with one indicator light:

| Status                               | Function   |
|--------------------------------------|--|
| The diode is emitting constant light | "No Signal" operation mode, the driver is not receiving any DMX signal |
| The diode is blinking                | A DMX signal is being received   |

# 5 DMX address setting

PX319 allows for setting the address DMX. The address is set in a binary code using the DIP Switch. Below are some examples of setting the DMX address. Nine first DIP Switches are responsible for the address; the tenth switch is responsible for activating the “smooth” function.



## 5.1 Smooth function settings




The “*smooth*” function active and DMX address set to 1.

With the *smooth* function enabled, transition between successive control signal values are smoothed, allowing for smooth changes in the brightness of the connected LEDs. This prevents the light “vibration” effect that usually occurs in lighting systems when light intensity is being changed.

## 5.2 No Signal function settings


The PX319 driver is equipped with an additional DIP Switch which allows to set the No Signal function, responding to the driver action when it does not receive the DMX signal.

With this switch, it is possible to set one of 4 brightness levels. The brightness increases from the smallest (zero) to the maximum one, in accordance with the binary markings on the DIP Switch. Below are brightness levels and the corresponding switch settings.




## 5.3 PWM frequency settings

It is possible to set PWM frequencies using individual switch position no. 3 on the small DIP Switch:



Zero brightness level and PWM frequency of 366Hz



Zero brightness level and PWM frequency >20kHz

## 6 Driver output current setting

---

The PX319 driver is equipped with a function to set the output current controlling linear LED modules. Depending on the number of modules connected to the device, it is necessary to select the control current by choosing a resistor with the appropriate resistance. The table on the next page shows the correct selection of resistors.

| Current limit | Resistor |
|---------------|----------|
| 250mA         | 100R     |
| 700mA         | 1k5      |
| 1000mA        | 3k       |
| 1300mA        | 5k1      |
| 1500mA        | 7k5      |
| 2000mA*       | 15k      |

\* - not applicable to the PX319-HV version driver


In the absence of any connection between resistor and PX319 driver, it will operate with adjusted 250mA output current (as for 100 Ω resistor connection).

Below is the table allowing for the selection of resistor bar-codes:


| Color  | Significant figures | Multiplier     | Tolerance | Temperature coefficient |
|--------|---------------------|----------------|-----------|-------------------------|
| None   | -                   | -              | 20%       | Irrelevant              |
| Silver | -                   | x0,01          | 10%       |                         |
| Gold   | -                   | x0,1           | 5%        |                         |
| Black  | 0                   | x1             | -         |                         |
| Brown  | 1                   | x10            | 1%        |                         |
| Red    | 2                   | x100           | 2%        |                         |
| Orange | 3                   | x1.000         | -         |                         |
| Yellow | 4                   | x10.000        | -         |                         |
| Green  | 5                   | x100.000       | 0,5%      |                         |
| Blue   | 6                   | x1.000.000     | 0,25%     |                         |
| Purple | 7                   | x10.000.000    | 0,1%      |                         |
| Gray   | 8                   | x100.000.000   | -         |                         |
| White  | 9                   | x1.000.000.000 | -         |                         |

Example of the resistor identification:

### Resistor 3K - 5% - E24




### Resistor 7K5 - 1% - E96



## 6.1 Temperature control

You can connect an external 4K7 thermistor to the driver. As the temperature exceeds 70°C, the driver starts to limit output power. Once a 90°C threshold is exceeded, complete shut off is carried out.


- if no NTC thermistor has been connected– 100% of power available at the output
- if NTC thermistor short circuit – 0% of power available at the output



## 7 DMX signal connecting


PX319 have to be connected to DMX line in serial mode, with no branches on DMX control cable. That means that DMX line, from the signal source, must be connected to **DMX in** pins of PX319 and later, directly from **DMX out** pins to the next device in DMX chain.

If the PX319 is the last DMX chain receiver there should be terminator (resistor 120 Ohm) mounted between “+” and “-” pins of **DMX out** section.





# 9 Dimensions



## 10 Technical data

---

|                                |   |
|--------------------------------|---|
| type                           | PX319   |
| DMX channels                   | 511   |
| power supply                   | 12 – 48V DC (PX319)<br>12 – 60V DC (PX319-HV)   |
| max. power consumption         | 2A (PX319) / 1,5A (PX319-HV)                    |
| no-load power consumption      | 0,5W  |
| number of output channels      | 1   |
| brightness levels of the scene | 8   |
| output load                    | 250 – 2000mA (PX319)<br>250 – 1500mA (PX319-HV) |
| output sockets                 | screw terminals                                 |
| weight                         | 0.15kg  |
| dimensions                     | width: 132mm<br>height: 47mm<br>depth: 21mm     |

## DECLARATION OF CONFORMITY

PXM Marek Żupnik spółka komandytowa  
Podłęże 654, 32-003 Podłęże

we declare that our product:

*Product name:* Driver LED C.C. 1 x 2A  
Driver LED C.C. 1 x 1,5A/hv

*Product code:* PX319  
PX319-HV

meets the requirements of the following standards, as well as harmonised standards:

|                             |                       |
|-----------------------------|-----------------------|
| PN-EN IEC 63000:2019-01     | EN IEC 63000:2018     |
| PN-EN 61000-4-2:2011        | EN 61000-4-2:2009     |
| PN-EN IEC 61000-6-1:2019-03 | EN IEC 61000-6-1:2019 |
| PN-EN 61000-6-3:2008        | EN 61000-6-3:2007     |

and meets the essential requirements of the following directives:

2011/65/UE **DIRECTIVE OF THE EUROPEAN PARLIAMENT AND OF THE COUNCIL** of 8 June 2011 on the restriction of the use of certain hazardous substances in electrical and electronic equipment  
Text with EEA relevance.

2014/30/UE **DIRECTIVE OF THE EUROPEAN PARLIAMENT AND OF THE COUNCIL** of 26 February 2014 on the harmonisation of the laws of the Member States relating to electromagnetic compatibility (recast)  
Text with EEA relevance.

  
**Marek Żupnik spółka komandytowa**  
32-003 Podłęże, Podłęże 654  
NIP 677-002-54-53



mgr inż. Marek Żupnik.