

Transmitter 1ch
flush-mounted
GORKE
(SPR-PW1/x/Z+B)



Device description

PY509 is a durability flush-mounted button. It has been designed in such a way that it can function in conditions of increased risk of damage to system components. The front panel is made of brushed stainless steel with a thickness of 2mm, and the button itself is mounted in a way that prevents it from being undermined (vandal-resistant). In addition, the button has a light and sound signaling of transmission.

The transmitter is powered by LS 14250 3.5V battery or from an external 9 – 28V DC power supply. Flush-mounted Transmitter 1ch can work with any sA series receiver.

The transmission is coded and is based on a variable code, which ensures high security when using wireless systems. Each transmitter has an individual code, and the receiver only reacts to signals that are received from the transmitters stored in its memory. PY509 can be assigned to an unlimited number of receivers.

Transmitter mounting can be surface-mounted, for this please order separately the Transmitter 1ch – plastic box (PY508).



Technical data

type	PY509
number of keys	1
frequency	433,92MHz
coding	variable code
cooperation	any sA series receiver
montage	flush
available colors	red / green / blue
backlight	yes
power supply	LS 14250 3.6V battery or 9 – 28V DC
weight	0.15kg
dimensions	width: 88mm height: 88mm depth: 40mm